

# **INSTRUCTION MANUAL**

## **MODEL 2005-10 Test Upconverter**

Data, drawings, and other material contained herein are proprietary to Cross Technologies, Inc., but may be reproduced or duplicated without the prior permission of Cross Technologies, Inc. for purposes of operating the equipment.

When ordering parts from Cross Technologies, Inc., be sure to include the equipment model number, equipment serial number, and a description of the part.

First Edition	<b>May 2000</b>	<b>Rev 0</b>
	<b>September 2006</b>	<b>Rev A</b>

**CROSS TECHNOLOGIES, INC.**  
**6170 SHILOH ROAD**  
**ALPHARETTA, GEORGIA 30005**

**(770) 886-8005**  
**FAX (770) 886-7964**

**WEB [www.crosstechnologies.com](http://www.crosstechnologies.com)**  
**E-MAIL [info@crosstechnologies.com](mailto:info@crosstechnologies.com)**

# INSTRUCTION MANUAL

## MODEL 2005-10 Test Upconverter

<b><u>TABLE OF CONTENTS</u></b>	<b><u>PAGE</u></b>
<b>Warranty</b>	<b>2</b>
<b>1.0 General</b>	<b>3</b>
<b>1.1 Equipment Description</b>	<b>3</b>
<b>1.2 Technical Characteristics</b>	<b>4</b>
<b>2.0 Installation</b>	<b>5</b>
<b>2.1 Mechanical</b>	<b>5</b>
<b>2.2 Front Panel Controls/Indicators</b>	<b>5</b>
<b>2.3 Rear Panel Input/Output Signals</b>	<b>5</b>
<b>2.4 Accessing the PC Card</b>	<b>6</b>
<b>2.5 Installation/Operation</b>	<b>6</b>

**WARRANTY** - The following warranty applies to all Cross Technologies, Inc. products.

All Cross Technologies, Inc. products are warranted against defective materials and workmanship for a period of one year after shipment to customer. Cross Technologies, Inc.'s obligation under this warranty is limited to repairing or, at Cross Technologies, Inc.'s option, replacing parts, subassemblies, or entire assemblies. Cross Technologies, Inc. shall not be liable for any special, indirect, or consequential damages. This warranty does not cover parts or equipment which have been subject to misuse, negligence, or accident by the customer during use. All shipping costs for warranty repairs will be prepaid by the customer. There are no other warranties, express or implied, except as stated herein.

**CROSS TECHNOLOGIES, INC.  
6170 SHILOH ROAD  
ALPHARETTA, GEORGIA 30005**

**(770) 886-8005  
FAX (770) 886-7964  
Toll Free 888-900-5588**

**WEB [www.crosstechnologies.com](http://www.crosstechnologies.com)  
E-MAIL [info@crosstechnologies.com](mailto:info@crosstechnologies.com)**


# MODEL 2005-10 Test Upconverter

## 1.0 General


### 1.1 Equipment Description

The 2005-10P Test Upconverter converts a 70 MHz or 140 MHz IF signal to 2000 to 2500 MHz in 1 MHz steps with selection of high side LO (C = inverted) or low side LO (Ku = non-inverted) and 70 or 140 MHz input over the 2.0 - 2.5 GHz range.

Featuring low phase noise, these units are used to loop 70 or 140 MHz modulators to 2.0 - 2.5 GHz receivers for test purposes. The 70 or 140 MHz carrier input is mixed with a synthesized local oscillator (LO) signal. The output frequency is selected with four BCD switches which control the synthesized LO. Front panel LEDs light when DC power is applied (green) and when a PLL alarm occurs (red). The mixer output is applied to the output attenuator providing a nominal gain of -10 dB (high gain) or -30 dB (low gain). Connectors are 50Ω BNC (female) for the IF input and for the RF output (other connector options are available). Wall power supply options are **-P** for 120 VAC, 60Hz, and **-P4** is 90-260 VAC. The 2005 can be mounted on a 1 3/4" X 19" rack mount panel (**option -R**).



**FIGURE 1.1 Block Diagram**



**FIGURE 1.2 Front and Rear Panel**

## 1.2 Technical Characteristics

**TABLE 1.0 2005-10 Upconverter Specifications\***

### Input Characteristics

Impedance	50Ω
Return Loss	15 dB
Frequency Level	70 or 140 MHz center, ± 20 MHz
	-10 to -25 dBm (LOW GAIN)
	-25 to -40 dBm (HI GAIN)
1dB compression	0 dBm (LOW GAIN)
	-15 dBm (HI GAIN)

### Output Characteristics

Impedance	50Ω
Return Loss	12 dB
Frequency Range	2.0 to 2.5 GHz

### Channel Characteristics

Gain	-30 dB ± 3 dB (LOW GAIN)
	-10 dB ± 3 dB (HI GAIN)
Spurious Response	< -40dBC max, < -45dBC typ; <b>OUTPUT NOT FILTERED</b>
Frequency Response	± 2 dB, 2.0 - 2.5 GHz; ± 0.5 dB, any 10MHz increment

### Synthesizer Characteristics

Frequency Accuracy	± 25 kHz max					
Frequency Step	1.0 MHz minimum					
Phase Noise	@ Freq	100Hz	1kHz	10kHz	100kHz	1MHz
	dBC/Hz	< -70	< -70	< -80	< -90	< -100

### Indicators

DC Power	Green LED
PLL Alarm	Red LED

### Other

RF, IF Connectors	BNC (female)
Size, Bench Top	4.7" wide X 1.75" high X 6.5" deep
Size, Rack Mount	19 inch standard chassis 1.75"high X 7.0" deep ( <b>option -R</b> )
Power	+14 to +24 VDC, 180 ma on RF Out
AC Power	120 ±10% VAC, 60 Hz, 10W max wall mount power supply ( <b>option -P</b> )

\*+10 to +40 degrees C; Specifications subject to change without notice

## 2.0 Installation


### 2.1 Mechanical

The 2005 is packaged in an aluminum extrusion. The **-R option** is mounted on a 1 3/4" X 19" panel that can be mounted to a rack using the 4 holes at the ends. The unit derives +DC from the RF out center conductor (+14 to +24 VDC) or the wall power supply (+15V unregulated, **option -P, -P4**). See Figure 2.3.

#### 2.1.1 Cleaning Instructions


Wipe the exterior with a dry, soft cloth. Use no detergent or cleaning chemicals.

### 2.2 Front Panel Controls/Indicators - Figure 2.1 shows front panel controls and indicators for the 2005-10.



**FIGURE 2.1 2005-10 Front Panel Controls and Indicators**

### 2.3 Rear Panel Input/Output Signals - Figure 2.2 shows the input and output signals to the 2005-10.




**FIGURE 2.2 2005-10 Rear Panel Inputs and Outputs**

## 2.4 Accessing the PC Card

There are NO USER JUMPERS or other on-card controls. ALTHOUGH IT IS NOT RECOMMENDED AND MAY VOID THE WARRANTY the following shows how to remove the printed circuit board (PCB) from the extrusion:

1. ALWAYS REMOVE POWER when installing or removing the PCB from the extrusion
2. Remove four (4) rear panel screws (see Figure 2.3).
3. GENTLY pull the rear panel and PCB assembly completely out of the extrusion.
4. To install the PCB, GENTLY push the rear panel and PCB assembly completely into the extrusion. Make sure the shield goes in the lower channel and the PCB in the next channel above that in the extrusion and that the front panel controls go through the front panel holes.
5. Install four (4) rear panel screws.



**FIGURE 2.3 2005 Assembly Drawing**

## 2.5 Installation / Operation

### 2.5.1 Installing and Operating the 2005-10

1. If using the receiver LNB voltage to power the 2005-10, be sure +14 to +24 VDC is on the RF center conductor. If using the wall power supply (**options -P or -P4**), connect the power supply to the DC POWER connector and either 120 VAC (**-P**) or 90-260 VAC (**-P4**) (Figure 2.2)
2. Select either C or KU band (SW6) and either 70 or 140 MHz IF (SW5) using the front panel switches (Figure 2.1).
3. Select either HI or LOW GAIN using the switch (SW7) on the rear panel (Figure 2.2).
4. Connect a -10dBm max (LOW GAIN) or -25 dBm max (HI GAIN) signal to IF In, J1 (Figure 2.2).
5. Connect the RF OUT, J2, to the receiver under test (Figure 2.2).
6. Set BCD switches, SW1 to SW4, to the desired frequency (Figure 2.1).
7. Be sure DS1 (green, DC Power) is on and DS2 (red, Alarm) is off (Figure 2.1).

**CROSS TECHNOLOGIES, INC.  
6170 SHILOH ROAD  
ALPHARETTA, GEORGIA 30005**

**(770) 886-8005  
FAX (770) 886-7964  
Toll Free 888-900-5588**

**WEB [www.crosstechnologies.com](http://www.crosstechnologies.com)  
E-MAIL [info@crosstechnologies.com](mailto:info@crosstechnologies.com)**